



MIVOICE OFFICE 400

FEATURE OVERVIEW

This document provides an overview of the features, that can be operated on the terminals, via Self Service Portal, via WebAdmin or via CTI.

Document number: syd-0595
Document version: 1.2
Valid as of / based on: R4.1 / R4.1

© 08.2016 Mitel Schweiz AG

Click on the following hyperlinks to download the latest version of this document:

As PDF:

https://pbxweb.aastra.com/doc_finder/DocFinder/syd-0595_en.pdf?get&DNR=syd-0595

As Excel:

https://pbxweb.aastra.com/doc_finder/DocFinder/syd-0595h_en.zip?get&DNR=syd-0595&RES=1

Feature Overview MiVoice Office 400 valid as of R4.1		Type				MMC and integrated mobile/ext. phones ¹⁾					Mitel 6700 SIP Mitel 6800 SIP					Standard SIP terminals					MiVoice 2380 IP MiVoice 1560 PC Operator					MiVoice 5300 / 5300 IP Office 10 ²⁾ ,25,35,45					Mitel 600 DECT Office 135 / 160					Mitel 600 SIP-DECT					ISDN terminals					Analogue terminals (DTMF)				
		Prefix dialling	Suffix dialling	In a call	During ringing	Supported					Supported					Supported					Supported					Supported					Supported					Supported					Supported									
						Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI	Phone	SSP	WA	TAPI	CTI					
Feature	Function code																																																	
Text messages: Send freely defined text message		•																																																
Text messages: Send to all with / without parameters	*3599 text No. #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Text messages: Send to group with / without parameter	*35 Gr. No. text No. #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Text messages: Send to user with / without parameter	*3598 user No. text No. #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Text messages: View		•																																																
Transfer charges of current call to another cost centre	*78 CC No.		•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Trigger Redkey function	*73 Parameter #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Two-company configuration for operator phones	Via line key	•																			• ³⁾	•																												
User groups: Log into all user groups	*4800	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
User groups: Log into specific user groups	*48 UG No.	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
User groups: Log out of all user groups	#4800	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
User groups: Log out of specific user groups	#48 UG No.	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
User-to-user signalling (UUS-1)																																																		
Voice mail: Activate greeting	*933 x	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•						
Voice mail: Check recording	*#913 x [*nn] # or *#923 x [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Deactivate greeting	#933 x	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•						
Voice mail: Delete recording	#913 x [*nn] # or #923 x [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Listen to voice messages with audio guide	*#94	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Listen to voice messages without audio guide	*#916 #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Recording a welcome announcement with a ph	*913 x [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Recording a welcome announcement with audi	*923 x [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Voice mail: Signalling of new messages											• ⁶⁾	•				•	•				•	•				•	•				•	•				•	•				•	•								

1) Mobile phone integration level 2 is required for features introduced with ***

2) Not all features are available for Office 10

3) Only MiVoice Office 5380 and Office 45

4) Only Mitel Mobile Client (MMC)

5) Only MiVoice Office 5300 / 5300 IP

6) Only Mitel 600 DECT

7) Without MiVoice Office 5360 / 5360 IP and Office 25

8) Only Mitel 600 DECT and Office 135/135pro

9) Only for internal calls and via soft key

a) Only Mitel 6710 / 6730 Analogue

b) Depending on the terminal

c) ISDN feature

d) Only via soft key

SSP = Self Service Portal, WA = WebAdmin

CTI TAPI: F= First-Party, T=Third-Party

Note:

You can activate certain function codes only if the samefunction cannot be obtained via the menu.

Function codes for SIP phones can only be carried out in prefix dialling.