

Feature Overview MiVoice Office 400 valid as of R4.1		Type				MMC and integrated mobile/ext. phones ¹⁾					Mitel 6700 SIP Mitel 6800 SIP					Standard SIP terminals					MiVoice 2380 IP MiVoice 1560 PC Operator					MiVoice 5300 / 5300 IP Office 10 ²⁾ ,25,35,45					Mitel 600 DECT Office 135 / 160					Mitel 600 SIP-DECT					ISDN terminals					Analogue terminals (DTMF)									
		Prefix dialling	Suffix dialling	In a call	During ringing	Supported	Operat- ing via				CTI	Supported	Operat- ing via				CTI	Supported	Operat- ing via				CTI	Supported	Operat- ing via				CTI	Supported	Operat- ing via				CTI	Supported	Operat- ing via				CTI														
							Phone	SSP	WA	TAPI			CSTA	Phone	SSP	WA			TAPI	CSTA	Phone	SSP			WA	TAPI	CSTA	Phone			SSP	WA	TAPI	CSTA			Phone	SSP	WA	TAPI		CSTA	Phone	SSP	WA	TAPI	CSTA	Phone	SSP	WA	TAPI	CSTA			
Feature	Function code																																																						
Making calls with your own settings on a third-party phone	#36 user No. PIN	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
Making calls with your own settings on a third-party phone	#46 user No. PIN	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
MESSAGE LED: Activate	*38	•	•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
MESSAGE LED: Activate	*38 user No.	•				•	•				•	•			T	•	•			T	•	•			T	•	•			T	•	•				•	•				•	•													
MESSAGE LED: Answer	*#38	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•								
MESSAGE LED: Clear (on the executing phone)	#38 user No.	•				•	•				•	•			T	•	•			T	•	•			T	•	•			T	•	•				•	•				•	•													
MESSAGE LED: Delete (on the destination phone)	#38 #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Music on hold: Check recording	*#914 [*nn] # or *#924 [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Music on hold: Delete recording	#914 [*nn] # or #924 [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Music on hold: Record with audio device	*924 [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Music on hold: Recording with the phone	*914 [*nn] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Open door	*74 <No. door intercom>	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Park / Retrieve: With line key			•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Park / Retrieve: With park key (local)			•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Park: Central	*76		•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Park: Connect with centrally parked user	#76	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Personal call routing: Activate	*45 x	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Personal call routing: Deactivate	#45	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
PIN telephony: Make external call	*95 x PIN dest.-Nr.	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
PIN telephony: Update external call	*959 x PIN		•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
PIN telephony: Update project call	*721 <Application ID code> PIN #		•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Presence status: Activate	*27 x #	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Presence status: Activate with time	*27 hh mm #	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Presence status: Activate with time and date	*27 x hh mm DD MM #	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Presence status: Deactivate	#27 or *27 0 #	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Private calls with PIN	#46 user No. PIN	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Records malicious calls (MCDI)			•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Remote control: Allow to own set		•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote control: Execute personal features	*06 user No. <function code>	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote control: Protect against		•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote maintenance access: Disable (once)	#754	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote maintenance access: Disable (permanent)	#753	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote maintenance access: Enable (once)	*754	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Remote maintenance access: Enable (permanent)	*753	•				•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Return to the call on hold	1		•			•	•				•	•			• ^{b)}	•	•			T	•	•			T	•	•			T	•	•				•	•				•	•													
Ring Alone: Activate	*41	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Ring Alone: Deactivate	#41	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Ringing relay with delay (line keys and team keys)						•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•		•	•	•	•											
Room monitoring (baby surveillance) Activate	*25 x user No. [* y] #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Room monitoring (baby surveillance) Deactivate	#25	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Send transparent data	*72 Parameter #	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Show call charges						•	•				•	•			F/T	•	•			F/T	•	•			F/T	•	•			F/T	•	•				•	•																		
Silent intrusion: Activate	4	•	•			•	•				•	•				•	•				•	•				•	•				•	•				•	•				•	•													
Silent intrusion: Activate	*63 user No. #	•																																																					

