

**CLASS Services
Feature Set 1
Quick Reference
Guide**
590-2549-001



EADS TELECOM North America



Caller ID Block

CALLER ID BLOCK



Dial *** 6 7**

System Responds:



CALLER ID BLOCK



Dial *** 8 2**

System Responds:




Anonymous Call Rejection

ANONYMOUS CALL REJECTION



Dial *** 7 7**

System Responds:




TO DEACTIVATE




Dial *** 8 7**

System Responds:



**Call Forward
With Voice Response**

CALL FORWARD



Dial **7 2 #**

System Responds:




Dial → **Destination Number**

Selected Line Forwarded

System Responds:

If Destination is Toll Call



Dial → **Authorization Code**

System Responds:



Selected Line Forwarded

**Call Forward - Deactivation
With Voice Response**

TO DEACTIVATE CALL FORWARD



Dial **7 3 #**

System Responds:




Call Forward Remote Access Deactivated

First Edition (February 14, 2003)
© Copyright 2003 EADS TELECOM North America
All Rights Reserved

**Automatic Recall With Confirmation
No Voice Response**

AUTOMATIC RECALL WITH CONFIRMATION

Display Phone, No IVS



Dial *** 6 9**

Display Shows:

972-555-5555 2:23pm
Call? Dial 1 5:33pm


or

Private 2:23pm
Call? Dial 1 5:33pm

or

Unavailable 2:23pm
Call? Dial 1 5:33pm

System Responds:




Dial **1**

Display Shows:

Enter Authorization Code 2:23
5:33pm


and

System Responds:



Dial → **Authorization Code**

System Responds:



Selected Incoming Call Dialed

5057 Keller Springs Rd.
Addison, TX 75001

Phone: 972.855.8000
Fax: 972.855.8071

Email: techpubs@eadstelecom-na.com

AUTOMATIC RECALL WITH CONFIRMATION



Dial

*	6	9
---	---	---

System Responds:



Date, Time, Number of Last Incoming Call

or



“Private”

or



“Unavailable”

and



“Please press 1 to complete or hang up to cancel your call.”

Dial

1

System Responds:



“Please enter the authorization code.”

Dial → Authorization Code

System Responds:



Calling xxx-xxx-xxxx.


Selected Incoming Call Dialed

ACTIVATE REMOTE FEATURE ACCESS




Dial → Remote Access Directory Number

System Responds:




Dial → Directory Number (DIRN)

System Responds:



Dial → PIN Number

System Responds:



Dial → Desired Feature Code

Call Forward

7	2	#
---	---	---

Anonymous Call Rejection


7	7	#
---	---	---

Selective Call Forward

6	3	#
---	---	---

Go to → Instructions for Specific Feature

ACTIVATE REMOTE FEATURE ACCESS



Dial → Remote Access Directory Number

System Responds:



“Please enter directory number.”

Dial → Directory Number (DIRN)

System Responds:



“Please enter Personal Identification Number.”

Dial → PIN Number

System Responds:



“Please enter the feature code.”

Dial → Desired Feature Code

Call Forward

7	2	#
---	---	---

Anonymous Call Rejection


7	7	#
---	---	---

Selective Call Forward

6	3	#
---	---	---

Go to → Instructions for Specific Feature

SELECTIVE CALL FORWARDING



Dial

*	6	3
---	---	---

System Responds:



“Selective call forwarding is on/off.”
 “There are x entries on your list.”
 “Your call will be forwarded to xxx-xxxx.”
 “If this number is correct, press 1.”
 “If this number is not correct, press 0 to change it.”
 and

“To hear the entries on your list, press 1.”
 “To turn on/off selective call forwarding, press 3.”
 “To add an entry to your list, press the # key.”
 “To remove an entry from your list, press * key.”
 “To hear these instructions again, press 0.”

Dial

1

System Responds:



“There are x entries on your list.”
 “The first entry on your list is xxx-xxxx.”
 “Next, xxx-xxxx.”
 Repeats for all numbers
 and
 Main Menu Repeats

Dial

3

System Responds:



“Please dial the number to which you want your calls forwarded, followed by the # key.”
Dial Number
 “Your calls will be forwarded to xxx-xxxx.”
 “If this number is correct, press 1.”
 “If this number is correct, press 0 to change.”
 “Selective call forwarding is on.”
 and
 Main Menu Repeats

Dial

#

System Responds:




“Dial the number to be added, followed by the # key.”
 “To add the previous caller to your list, press 01 followed by the pound key.”
Dial Number
 “The number you have added is xxx-xxxx.”
 and
 Main Menu Repeats

Dial

*

System Responds:



“Dial the number to be removed followed by the # key.”
 “To remove the number of the previous caller, dial 01 followed by the # key.”
 “To remove all entries from the list, dial 08 followed by the pound key.”
 “To remove all private entries from the list, dial 09 followed by the # key.”
Dial Number
 The number you have removed is xxx-xxxx.
 and
 Main Menu Repeats

Automatic Recall With Confirmation With Voice Response

Activate Remote Feature Access With No Voice Response

Activate Remote Feature Access With Voice Response

Selective Call Forwarding



EADS TELECOM North America

© Copyright 2003 EADS TELECOM North America
 All Rights Reserved

© Copyright 2003 EADS TELECOM North America
 All Rights Reserved